



ECB50A Circuit Breaker Finder and AC Cable Tracer

Three testers in one

- Identify circuit breaker to an electrical socket
- Trace AC cables in walls
- Sort wires in a bundle
- Microprocessor controlled
- Coded transmission allows easy separation of transmitter signal
- Audible and visual indicators
- Low battery indicator
- Cable tracing depth up to 40 cm
- NEMA 5-15 plug

Included Accessories Padded carrying case, 9V battery, user's manual



Data Sheet

battery, user's manual



www.Amprobe.com

No hassle warranty

NO HASSLE

POGRA

No waiting.

No shipping charges.

Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)

Amprobe® Test Tools



ECB50A Circuit Breaker Finder and AC Cable Tracer

Data Sheet

General Specifications

Transmitter	
Operating temperature range	-10 °C to 40 °C (14 ° to 104 °F) at max 80 % R.H.
Dimensions	70 x 55 x 86 mm (2.8 x 2.1 x 3.4 in)
Weight	Approximately 65 g (2.3 oz)
Overvoltage category	CAT III 150 V
Pollution degree	2, Protection Class: IP20
Receiver	
Sensitivity setting	Using On/Off control
Low battery indication	7.5 V
Switching fuse/cable	manually using Fuse-Line switch
Operating temperature range	-10 °C to 40 °C (14 ° to 104 °F) at max 80 % R.H.
Dimensions	22 x 162 x 34 mm (0.9 x 6.4 x 1.3 in)
Weight	Approximately 100 g (3.5 oz)
Overvoltage category	CAT III 300 V
Pollution degree	2, Protection Class: IP20
Power supply	9 V battery, IEC 6LR61, Alkaline only
Applicable directives	EMC: EN 50081-1 and EN 50082-1, EN61010-1:2001
and standards	

Specifications (Valid for 23 $^{\circ}C \pm 5$ °, for less than 80 % relative humidity)

Transmitter	
Voltage range	100 V to 250 V
Power consumption	approximately 1 W
Frequency range	50/60 Hz
Transmission frequency	Approximately 8 kHz
Transmitter frequency	Approximately 10 Hz
Receiver	
Tracing depth for fuse	Approximately 0 to 10 cm (4 in) depending on local conditions
identification	
Tracing depth for cable location	Approximately 0 to 40 cm (15 in) depending on local conditions

Amprobe® Test Tools

website: www.Amprobe.com email: info@amprobe.com Everett, WA 98203 Tel: 877-AMPROBE

Amprobe® Test Tools Europe

In den Engematten 14 79286 Glottertal, Germany Tel.: +49 (0) 7684 8009 - 0

> ©2007 Amprobe Test Tools. All rights reserved. 9/2007 2123465 D-ENG-N Rev B

Amprobe® Test Tools

www.Amprobe.com